



T.			U_f		I_f	$U_b=U_I$	R_a	U_g	I_a	I_I	α°	$U_{a(max)}$	$U_{I(max)}$	$U_{I(min)}$	U_{flik}
			V	A											
AM 1	eur	1	4	0,3	200	2	0 ÷ -4	75 ÷ 20	0,13	20 ÷ 90		250	275	125	100
EM 1	eur	1	6,3	0,2	250	2	0 ÷ -5	95 ÷ 20	0,13	16 ÷ 90					
EM 31	Mul	2	6,3	0,2											
FT 4	Fer	2	4	0,5	250	2	0 ÷ -6		0,5						
ME 4	Tu	1	4	0,3	250	2	0 ÷ -5	1000	1,3	90 ÷ 0					
ME 6	Tu	1	6,3	0,2											
ME 4 S	Tu	1	4	0,3	250	2	0 ÷ -5	120	2	90 ÷ 0		250	250	200	100
ME 6 S	Tu	1	6,3	0,2											
2 E 5	amer	3	2,5	0,8	125	1	0 ÷ -4,5	100	0,8	90 ÷ 0		250	250	125	90
6 E 5	amer	3	6,3	0,3	250	1	0 ÷ -7,5	200	2	90 ÷ 0					
6 E 5-GT	int	2	6,3	0,3	100	0,5	0 ÷ -3,3	190	1	90 ÷ 0					
6 E 5 C	CCCP	4	6,3	0,3	200	1	0 ÷ -6,5	190	3	90 ÷ 0					
6 S 5	amer	5	6,3	0,3	250	1	0 ÷ -8	240	4	90 ÷ 0		250	250	100	90
1629	int	2	12,6	0,15											

Equivalents


AD 77	Dar = AM 1	HF 3110	RFT = 6 E 5	TV 4	6 EG 5	eur = 6 E 5
AW 6	eur = EM 31	OSW 3110	RFT = 6 E 5	TV 6	6 S 5-G	Vis = 6 S 5
A 4-CAT	Cas = AM 1	TH 1	Dar = AM 1	U6-CAT	6 X 6	amer = 6 E 5-GT
ED 78	Dar = EM 1	TK 406	Tri = AM 1	VEM 1	6 X 6-G	amer = 6 E 5-GT
E 1180	Marc = EM 31	TK 606	Tri = EM 1	V 4678	41 ME	Cos = AM 1
					4678	Phil = EM 1




EM1




EM31



6E5



6E5C



6S5

